

L10-ET-CEC

10 Watt UL Listed LED Emergency Driver - Extended Temperature



Specifiers reference:

Project: _____

Type: _____

Model #: _____

Comments: _____

Product Summary

Approvals	UL Listed to UL924
Input	(Universal) 115 - 277Vac, 50/60 Hz
Input current	140 mA (max.)
Input power	10 Watts (max.)
Output voltage	15-55 Vdc - Class 2 Compliant
Output power	10W Constant Power
Operating time	90 minutes
Battery	Lithium
Test Switch	Quick Connect IP65 rated illuminated test switch
Weight	2.3 lbs.
Case	Galvanized steel
Dimensions	9.5" L x 2.4" W x 1.46" H
Operating Temperature	-4° to 131° F (-20° to +55° C)
Recharge time	24 Hrs
Warranty	5 years full

Description

The Assurance Emergency Lighting L10-ET-CEC LED emergency drivers are used with LED luminaires and Class 2 LED drivers to convert lighting fixtures for emergency lighting applications. The L10-ET-CEC provides extended temperature operation from -20°C to +55°C.

Specifications

Emergency lighting shall be provided by using a standard LED fixture, separate LED Class 2 driver and a constant power L10-ET-CEC 10W emergency LED Driver. The LED emergency driver shall be UL Listed for field or factory installations. It allows the LED luminaire to be used for both normal and emergency operation. The luminaire can be used for switched or unswitched applications. The L10-ET-CEC emergency driver is available with battery, charger and DC converter in a metal can. The L10-ET-CEC emergency driver shall provide a constant 10 watts to the LED load for a minimum of 90 minutes, and will operate over an extended temperature range of -20°C to +55°C. A quick connect IP65 rated test switch shall be included. The L10-ET-CEC shall have 10 watts of input power (max). The L10-ET-CEC meets or exceeds all National Electrical Code and Life Safety Code Emergency Lighting requirements and is rated for damp locations. The L10-ET-CEC LED emergency drivers are warranted for a full 5 years from date of purchase. The L10-ET-CEC meets Title 20 CEC requirements.



Mounting Configurations

L10-ET-CEC: No flex conduit



Note: Output current of AC driver must not exceed 5.0A

All Specifications subject to change without prior notification.

Assurance Emergency Lighting, a division of Assurance Engineering LLC

Assurance Engineering LLC · 357 Cumberland Street · Memphis, TN 38112 · 1-877-774-4775 · www.assurancelighting.com