

Si-250

250 Watt Pure Sine Wave Self Testing Emergency Lighting Inverter with Optional Power Share Technology



Compatible with LED loads

Specifiers reference:

Project: _____

Type: _____

Model #: _____

Comments: _____

Product Summary

- Approvals** UL Listed to UL924
- Input Voltage** Field Select-able 120 or 277 Vac input/Output
- Input Current** 2.7A (120 Vac), 1.2 A (277Vac)
- Input Frequency** 60 Hz
- Power Factor** 0.5 Leading to 0.5 Lagging
- Output** 120-277 Vac, 60 Hz
- Output Current** 2.0 A (120 Vac), 0.9A (277 Vac)
- Output Power** 250 W
- Output voltage regulation in emergency** +/- 5%
- Output** Dimmed, Switched, Normally On, & Normally Off
All models have 3 switchable command zones and 1 normally ON circuit.
- Operating Time** 90 Minutes @ 25°C
- Self-Testing & Self-Diagnostic**
Monthly reported via visual user interface panel
- Transfer Time** 50 msec
- Recharge Time** 24 Hours
- Battery over voltage and under voltage protection**
- Sealed long-life, valve-regulated, lead calcium batteries**
- Dimensions** 17.3"H x 15.4" W x 4.25"D
- Weight** 57 lbs.
- Operating Temperature** 68°F to 86°F (20°C to 30°C)
- Storage Temperature** -4° F to 158 °F (-20°C to 70°C)
- Warranty** 2 years full on electronics,
4 years pro-rata on batteries,
See website for warranty details

Options



- PST 3 Independent Adjustable (20-100%) Dimming Zones, 0-10Vdc, Dali, & Fire Alarm Interface (Max. Normal Power Load of 375W when using Power Share Technology PST)

Examples: Si-250 & Si-250-PST

Description

The Assurance Emergency Lighting Si-250 is a sine wave output self-test/self diagnostic inverter designed for designated emergency lighting fixtures. In the event of a power failure, the inverter will automatically supply 250 watts of emergency power to LED, fluorescent and incandescent luminaires for ninety (90) minutes. It will operate with multiple switched, non-switched and emergency only luminaires. It has optional features such as Power Share Technology (PST) for auto dimming in emergency, audible alarm and Seismic Restraints.

Specifications

Emergency lighting shall be provided by the Assurance Si-250 inverter unit equipment designed to operate designated LED and fluorescent fixtures on emergency power either at rated power or reduced luminaire power using the optional Power Share Technology during the 90 minute emergency discharge regardless of the wall switch position. The inverter shall allow for connected emergency fixtures to normally on, normally off dimmed/switched without affecting lamp operation during a power failure. The unit shall include a self-contained inverter section with an automatic, variable-rate battery charger, low voltage battery disconnect, short circuit, brown out protection and 5X crest factor for high inrush currents. The unit shall utilize a valve regulated sealed lead calcium battery with a 10 year design life expectancy. The inverter shall be self testing and self diagnostic and perform monthly self diagnostic test and report failures via user interface panel. The Si-250 shall have the option of Power Share Technology- which dims the load in emergency via the 0-10 vdc luminaire inputs to pre-selected values (20, 40, 60, 80 & 100%) for 3 independent zones. The inverter shall be UL Listed. It shall meet or exceed the requirements of UL924, NFPA 101 Life Safety Code, NFPA 70 National Electrical Code, OSHA, State and Local Codes. Warranty: Two (2) years full on electronics and four (4) years pro rata on batteries. Per the California Energy Commission, Regulatory Advisory dated Oct. 31, 2018, Backup Battery Charger Systems, the Si-250 is applicable and accepted for use in California.

Contact Customer Service for details regarding extended run time applications.

All Specifications subject to change without prior notification.

Assurance Emergency Lighting, a division of Assurance Engineering LLC

Assurance Engineering LLC · 357 Cumberland Street · Memphis, TN 38112 · 1-877-774-4775 · www.assurancelighting.com

06092021